



# Remote Indicating Lamp

## Remote Indicating Lamp

### Features

This unit is designed to ensure that alarm signal can be actually transmitted to all locations in order to prevent any missing signal caused by separated zones. Especially for the closed room, any fire condition happened can be transmitted to outside for pre-fire alarm notification.

### Construction and Characteristics

- Enlarged indicating lamp. (FG-91213)
- Build-in FLASH light, higher lumination and longer operating life. (FG-91213)
- Parallel type wiring.
- Low current consumption, so with 24VDC/2A control panel it can connect with up to 10 of FG-91213 or 100 of FG-01313.
- Individual revert switch. (FG-91213)



FG-01313

FG-91213

### Specification

Model	FG-91213	FG-01313
Power Source	24V DC	24V DC
Standby Current	24V DC 12mA	N/A
Alarm Current	160mA	12mA
Ambient Temperature	-10°C ~ +55°C	
Material	Fire-proof plastic	
Dimensions (HxWxD)	120mmx120mm x42mm	70mmx70mm x15mm
Weight	About 140g	About 32g
Color	White surface/ Red lamp cover	White surface/ Red LED

### Wiring Diagram

Fire Alarm Control Panel

